

Light-Drive Jog RGB/DW

Light-Drive RGB

Technical Specifications & Options

L x W x H:
 RGB
 100mm x 170mm x 45mm /
 3.93 x 6.69 x 1.77 inch
 Jog (RGB & DW)
 100mm x 115mm x 43mm /
 3.93 x 4.53 x 1.69 inch

Weight:
 RGB
 270g / 0.59 lbs
 Jog (RGB & DW)
 175g / 6oz

Power Input:
 Ext. Power supply: 9 to 24V DC
 PoTX (Power over TX Connect Data):
 Power-back via RJ45 from
 TX Connect Smart products

Power consumption:
 1.5W max.

Output ports: 2 x RJ45

Zones:
 RGB
 2 controllable zones
 Jog (RGB & DW)
 1 controllable zones

DMX Channels:
 RGB
 Output1: 1-510 (Zone1 and Zone2)
 Output2: 256-510 (Zone2)
 Jog (RGB & DW)
 512 channels (DMX512) duplicated
 on output 1 and output 2

Light-Drive JOG

Light-Drive Jog is a wall-mounted standalone DMX512 controller and interactive user interface for dynamic lighting with RGB or white fixtures. End-users can easily control color, intensity, and speed, by simply turning the Jog's wheel, easily adjusting the mood of any lighting scenario. Available in an RGB or Dynamic White (DW) version, Light-Drive Jog is a plug'n'play device idea for controlling lighting installations with no programming required.

- User-friendly standalone DMX512 controller
- Continuous replay of color sequences
- RGB or dynamic white option
- Simple set up
- Wall mountable
- No software needed

Light-Drive RGB

Light-Drive RGB is a wall-mounted standalone DMX512 controller and interactive user interface for dynamic lighting with RGB fixtures. With a simple turn of the wheel, end-users can directly control color, intensity, and speed, in up to two lighting zones, to easily adjust the ambiance of a lighting scenario. Six memory keys allow precise individual settings to be saved and recalled at any time with the simple press of a button, or via IR Remote Control. Additionally, two sequencing modes facilitate continuous replay of saved color settings and preset color phases or a dimmable white mode. A Plug'n'Play device, Light-Drive RGB promotes simplicity, controlling lighting installations with no programming required.

- User-friendly standalone DMX512 controller
- Six memory keys and multi-dimensional wheel
- Control up to two lighting zones
- Continuous replay of color sequences
- Dimmable white mode selection
- Simple set up
- Wall mountable
- No software needed
- Optional remote control



Light-Drive RGB



Light-Drive Jog RGB